



ALLIANCE

OUTDOOR LIGHTING

TREEMOUNT - MOUNTING INSTRUCTIONS

TREEMOUNT: Fixture Installation Accessory, Aluminum, Black Overcoat, 1/2" MPT, Junction Box Mount

The Alliance **TREEMOUNT** is attached with standoff screws to the main tree trunk or sturdy branch, which allows the tree to grow and helps prevent the **TREEMOUNT** from getting consumed by the tree itself. Be sure to allow two inches of tree growth room, when possible.



The **TREEMOUNT** can be used for properly securing both down lighting fixtures (such as DL100/DL200-LED or BT) in a tree to illuminate the surrounding area at the base of a tree, as well as securing up light fixtures (such as BL200/BL400-LED or BT) to illuminate the canopy of a large tree.

- Each **TREEMOUNT** will provide a mounting location for one fixture with a 1/2" male thread.
- The fixture wire connection can go inside the **TREEMOUNT**. Run wire up the non-visible or least-visible side of the trunk and fasten the low voltage wire to the trunk with specialized cable ties and stainless steel screws, making sure that the wire can still move with the tree. Leave some extra wire at the base of the tree to allow for tree growth.



Visit AllianceOutdoorLighting.com for more info.